

## PLUG 'N' PLAY EMERGENCY PACK FOR LED PRODUCTS

Convert any LED Panel to an Emergency Standard Panel



### FEATURES:

- Universal LED Emergency Pack allows electricians to convert an LED panel, or similar LED product to an Emergency Standard
- Simple and quick installation within 3 minutes, much faster than other
- Emergency conversion kits on the market
- Can be used with other LED products
- Three hour operation time

### APPLICATIONS



COMMERCIAL



FACTORIES



INDUSTRIAL



WAREHOUSE

# PLUG 'N' PLAY EMERGENCY PACK FOR LED PRODUCTS

Convert any LED Panel to an Emergency Standard Panel

<b>Part No.</b>	<b>243502</b>
<b>DESCRIPTION</b>	3 Hour LED Emergency Module
<b>DIMENSIONS (L-W-D)</b>	207 x 48 x 33mm
<b>POWER INPUT</b>	230-240V AC
<b>COLOUR</b>	Green LED Emergency Indicator
<b>CURRENT</b>	37mA
<b>LED TYPE</b>	DIP
<b>FIRE RESISTANT</b>	No
<b>IP RATING</b>	IP20
<b>CONSTRUCTION</b>	Plastic
<b>WORKING TEMPERATURES</b>	-20°C to +40°C
<b>LIFETIME</b>	50,000 hours
<b>SWITCHING CYCLES</b>	50,000
<b>ENERGY CONSUMPTION</b>	4.8 kWh
<b>DRIVER</b>	Any LED Product Driver
<b>CERTIFICATION</b>	CE, RoHS
<b>WARRANTY</b>	1 year (+ 4 years extended warranty with online registration) <b>Battery 2 years only</b>



**BRIGHT SOURCE**



Formerly rated A+  
(same quality,  
new energy rating  
label regulations)

